

Four-Bay Battery Charger

For Motorola APX Radios



*radio and battery not included

**INNOVATIVE ENGINEERING
AND MANUFACTURING
FOR OVER 30 YEARS**

305-623-3939
1-800-881-8211
jlopez@advancetec.com
www.AdvanceTec.com



PRODUCT FEATURES:

- Fast charging 4 Motorola batteries at the same time.
- Charge at current rates recommended by the battery manufacturer.
 - Be suitable to operate at the office (AC) as well as in the vehicle (DC).
 - Switch to a maintenance mode once the battery is fully charged. Charger will monitor battery voltage in order to keep its full capacity without ever overcharging or overheating.
- Mounting holes for wall mount

PRODUCT SPECIFICATIONS:

- Dimensions: 14 in. x 7.5 in. x 2 in.
 - Weight: 1.5 lb \pm 5%
- Operating temperature: 0°C to +40°C
- Storage temperature: -40°C to +85°C
- Relative humidity: 95% maximum non condensing
 - Power supply :
Input : 115VAC-230 VAC , OUTPUT : 15VDC 4A
Cord: 6 ft 22 AWG x 2C, 90C
- Charger Input : 2.5 mm center positive: 12VDC-24VDC \pm 20% , 4A \pm 10%
- Switching charging circuit: on board to minimize heat generation
- Charging system (each charging bay) : 1Amp , 4.2 VDC \pm 0.1%